

HIGH POWER / MIXERS / STUDY

MIX-8PRO

STUDIO MIXER.



- ✓ 8 channels and 2 outputs with independent volume controls
- ✓ USB player/recorder
- ✓ 16 digital effects processor
- ✓ USB audio for connection to PC as audio card



+ Info:
<https://fonestar.com/MIX-8PRO>

ESPECIALLY RECOMMENDED IN:



Hospitality



Sports facilities



Education



Hotels

DESCRIPTION

Professional 8-channel stereo mixer with PC audio card, USB recorder/player and Bluetooth® receiver. Connect the mixer to your PC as a Plug and Play audio card on Windows and Mac. You can play audio content from your PC via USB connection. USB player and recorder, play music or record the event without the need of a PC. It includes a 24-bit digital effects processor (16 effects), which will give an extra touch of quality to your events. In addition, 48 V phantom power supply is available for the use of condenser microphones. Ideal for use at all kinds of events, press rooms, live performances, concerts, etc.

TECHNICAL CHARACTERISTICS

FEATURES	<p>Professional 8-channel, 2-output mixer with independent volume controls.</p> <p>USB audio input for PC connection as Plug and Play audio card on Windows and Mac, allows audio playback from PC.</p> <p>4.2 Bluetooth Receiver</p> <p>USB recorder/player.</p> <p>16 digital effects processor.</p>
USB PLAYER	<p>Playback formats: WAV and MP3</p> <p>MP3 recording</p> <p>USB port for USB stick connection or PC connection as Plug and Play audio card under Windows and Mac</p> <p>Supports memory up to 128 GB</p>
INPUTS	<p>8 balanced XLR mics, 600 Ohm 2 mV (LED peak, 1 kHz, 20 mV RMS)</p> <p>8 unbalanced lines, 6.3 mm jack, 47,000 Ohm 45 mV (LED peak, 1 kHz, 180 mV RMS)</p> <p>2 balanced returns, 2 x 6.3 mm jack, 47,000 Ohm 300 mV RMS</p>
OUTPUTS	<p>1 stereo main (2 x XLR or 2 x 6.3 mm jack), 5 V RMS</p> <p>1 stereo line, 2 x RCA, 5 V RMS</p> <p>1 post-fader send, 6.3 mm jack, 5 V RMS</p> <p>1 stereo headphone, 6.3 mm jack</p>



+ Info:

<https://fonestar.com/MIX-8PRO>

CONTROLS	<p>Mic/line: low-cut filter (18 dB/octave, 75 Hz), gain, bass (± 15 dB, 80 Hz), mid (± 15 dB, 2,500 Hz), treble (± 15 dB, 12,000 Hz), aux/EFX send, pan, mute and slide volume control</p> <p>USB recorder/player: mode, play/pause/rec, song forward/reverse, bass (± 15 dB, 80 Hz), treble (± 15 dB, 12,000 Hz) and slider volume control</p> <p>Main: sliding volume control</p> <p>Phones: volume control</p> <p>Post-fader aux send: volume control</p> <p>Aux returns: volume control</p> <p>DSP effects processor: effect selection, repeat and slider volume control</p>
FUNCTIONS	<p>Sliders per channel</p> <p>3-band EQ on channels 1 to 8</p> <p>2-band equaliser on USB recorder/player</p> <p>Overload and master output level indicator lights</p>
PHANTOM	48 V, selectable
RESPONSE	20-20,000 Hz
DISTORTION	Harmonic: 0.07 %
S/N RATIO	> 65 dB
POWER SUPPLY	100-240 V AC, 20 W maximum
DIMENSIONS	390 x 85 x 320 mm depth
WEIGHT	3.8 kg
OPTIONAL	SM-8PRO: mounts for assembly in 19" rack



+ Info:
<https://fonestar.com/MIX-8PRO>